

?

????????? ?????????????? ??????? (UPS 103003270-6591) EATON 5115RM
750



750??,500?? ,V=220-240?

????????: ??? ???????
????:

[???????? ?????? ?? ????? ??????](#)

?????????????: [EATON](#)

?????????

????????????? ??????????????

????????? 750 ??

??? ??????? 103003270-6591 10

????????? (?? /??) 750 /500

?????????, ?*?* (??) 440*580*45

????? (??) 15

???????? ?????? IEC320 /10A

????????? ??????? 4*IEC320 /10A

????????? ?????? ?????????????? (??? ?????? ??????????)

(??? ?????????? 50%)

6 ???.

17 ???.

????????????????? ??????????????

????????????? ??????? ??????????? 220 /230 /240 ? ?????????????? ????

????????? ?????????? ??????????? ± 20% ?? ??????????

????????? ????????? 50 /60 ??, ?????????????????? ??????

????????????? ?????????? ??????????? 220 /230 /240 ? ?????????????? ????

?????????? ?????????? ?????????? -10% /+ 6% ?? ?????????? ?????????????? ??????????

?????????? ?????????? 110% — 3 ???.; 150% — 10 ??????

??? 95%

????????? ??????????????

?????????? ?? ??., ??? ????????? ?? ???????, ??????????, ?????????? ??????????????

????????????? ?????????????????? ?????? RS232 /USB ? X-slot

?????????????? ??????????? ??????? SNMP

???????? ??????

????????? ?????????????? 0°C — +40°C

????????????? ?????????? -15°C — +55°C

???????

????????? ????

???????????

????????????? CE

?????????????? IEC 62040 -1-1 ? UL 1778

EMC IEC 62040 -2, EN 6100 -3 -2

?????? ?????????????????? ????????? (???.)

????????? (??/??) 500 ?? 750 ??

200 /128 38

300 /192 27

500 /320 14

600 /400 9

750 /500 6

???????

??? ????????? ?? ????. ??????.