

?

????????? ?????????????? ??????? (UPS 103003276-6591) EATON 5115RM 1500



1500 ??,1000??,V=220-240?

????????: ??? ???????
????:

[???????? ?????? ?? ????? ??????](#)

?????????????: [EATON](#)

????????

????????????? ??????????????

????????? 1500 ??

??? ??????? 103003276-6591

????????? (?? /??) 1500 /1000

?????????, ?*?* (??) 440*580*45

????? (??) 19

???????? ??????? IEC320 /10A

????????? ??????? 4*IEC320 /10A

????????? ?????? ??????????????? (??? ?????? ??????????)

(??? ????????? 50%)

5 ???.

15 ???.

????????????????? ??????????????

????????????? ??????? ?????????? 220 /230 /240 ? ????????????? ????

????????? ?????????? ??????????? $\pm 20\%$?? ?????????

????????? ??????? 50 /60 ??, ?????????????? ??????

????????????? ?????????? ?????????? 220 /230 /240 ? ????????????? ????

????????????? ?????????? ?????????? -10% /+ 6% ?? ?????????? ????????????? ??????????

????????? ?????????? 110% — 3 ???.; 150% — 10 ??????

??? 95%

????????? ??????????????

????????? ?? ??., ?? ???? ?? ?????, ?????????, ????????? ??????????????

????????? ?????????????????? ????? RS232 /USB ? X-slot

????????? ?????????? ?????? SNMP

?????? ??????

?????? ?????????? 0°C — +40°C

????????? ?????????? -15°C — +55°C

?????? < 3000 ?

?????? ??? < 40 ?? ?? ?????????? 1 ?????

?????????

????????? CE

????????? IEC 62040 -1-1 ? UL 1778

EMC IEC 62040 -2, EN 6100 -3 -2

????? ?????????????? ??????? (???)

???????? (??/??) 1500 ??

200 /128 76

300 /192 58

500 /320 28

600 /400 19

750 /500 14

900 /600 10

1000 /670 8

1200 /800 6

1500 /1000 5

??????

??? ??????? ?? ??? ??????.