

?????????????? ?? G.711 ??? ??????? ?????, ??????????????? ??? ???????-?????? ??????? ?? ????? V.17, V.21, V.27ter, V.29 ??? ????-????
 ??????????? T.38

?????????? ??????? ??????????????? ?? ??????????????? ??????? ??????????????? ?????????, ?????????????? ? ??????????????? ???????, ??????? ??
 ????????????????? ????????? ???????, ?????????????????, ??????? ????????? ?????????, ????????????????? ???????????-?????, ??????? ??????? ?????????????
 ??????????? ???????, ????????????? ??????, ????????????????? ??????????? ??????????????? ??????????? (NEON LED) ? ??????????????? ???????, ?????????????
 QoS DiffServ, TOS, 802.1P/Q VLAN ??????????????

??????? ????????? TCP/UDP, RTP/RTCP, HTTP/HTTPS, ARP, ICMP, DNS, DHCP, NTP, TFTP, TELNET, PPPoE, STUN

????? DTMF ?????????????? ?????? ?????????? DTMF, ???????? In-audio, RFC2833, ?/??? SIP INFO

???????? SIP (RFC 3261) ?? UDP/TCP/TLS

?????? ???? SIP ? ?????? ????? ???? ?????? ?????? 4 ??????? ?????? ?????? SIP ??? ?????? ?????? ? ??????? ??????
 ?????? SIP ??? ?????? ?????????? ?????

Provisioning TFTP, HTTP, HTTPS, TR069

???????????? ???? SRTP, TLS/SIPS, H

?????????? Syslog, HTTPS, ???-???????, telnet, ?????????? ???? (IVR), TR-069

???????????? ???? ???? ???? ???? ?

- GXW4232/4224/4216: ?????: 12 ? ??????????? ?????, 5 ?; ?????: 100 ~ 240 ? ??????????? ?????, 50 ~ 60 ??
- GXW4248: ?????: 24 ? ??????????? ?????, 6,25 ?; ?????: 100 ~ 240 ? ??????????? ?????, 50 ~ 60 ??

????????????? ????????? ???? ?????: 0°C ~ 45°C; ??????: -20°C ~ 60°C; ??????: 10% ~ 90% (?? ??????)

????????????? ?????????????? ? ?????? ?? ?????????????? (????????????? ITU-T K.21, ??????? ????????? ??????????)

????????? ?????????????? ?????? ??????????????:

- 440 ?? (?) x 255 ?? (?) x 44 ?? (?) (1U) (GXW4248)
- 440 ?? (?) x 185 ?? (?) x 44 ?? (?) (1U) (GXW4216/4224/4232)

????????? ?????????? ?? ?????? ? ? ??????? ? ?????????? ?????????? ???????????????

??????? ? ???????? ?????? 2 REN, ?? 450 ?????? ??? ???????? 24 AWG

????? ???????????? ?????????? Bellcore ??? 1&2, ETSI, BT, NTT, ? CID ?? ?????? DTMF

?????? ?????????? ??????? "???????", ??????????/????????????????? ???????????, ??? ? ????????

????????????? ??????????? ???????????? ???????????? ?????????? ?????? ????: ?????? 15 (CFR 47) ?????? B ?????? ?????????: EN55022 ??????

B, EN55024, EN61000-3-2, EN61000-3-3, EN60950-1, RoHS C-TICK: AS/NZS CISPR 22 ????? B, AS/NZS CISPR 24, AS/NZS 60950 ITU-T K.21 (??????? ??????? ?????????); UL 60950 (??????? ????????)

??????

??? ??????? ?? ????? ???????.